

DOUGLAS COUNTY FAIRGROUNDS ARENA SPORTS LIGHTING

Pinenut Road Gardnerville, NV 89410

> Permit Set April 15, 2020







UNTY FAIRGROUNDS PORTS LIGHTING

REVISIONS

SHEET TITLE

PAIN. TP

 CHECKED:
 JEG

 DATE:
 4/15/20

 JOB NUMBER:
 19058

 PROJECT MGR:
 NA

G0.1

SUBSTITUTION: DEFINITIONS

OR EQUAL = EQUAL OR SUPERIOR TO SPECIFIED IN ALL RESPECTS WILL BE ALLOWED. ENGINEER'S PRE-BID APPROVAL IS NOT REQUIRED. PROPOSED EQUAL FIXTURES ARE SUBJECT TO REVIEW DURING THE STANDARD SUBMITTAL PROCESS.


• NO EQUAL = PROVIDE SPECIFIED FIXTURE. SUBSTITUTIONS ARE NOT ALLOWED.

SUBJECT TO REVIEW = EQUAL OR SUPERIOR TO SPECIFIED IN ALL RESPECTS MAY BE ALLOWED ONLY WITH ENGINEER'S APPROVAL. ALL SUBSTITUTIONS MUST BE SUBMITTED AS REQUIRED BY SPECIFICATIONS AND ACCOMPANIED WITH POINT BY POINT LIGHTING CALCULATIONS. DETERMINATION OF EQUAL IS ENGINEER'S SOLE DISCRETION.

TYPE	SYMBOL	DESCRIPTION AND MANUFACTURER
[] 10500 M	**	MUSCO TOTAL LIGHT CONTROL (TLC FOR LED TECHNOLOGY). 80' POLE WITH (7) 1500W HEADS. FULL CUTOFF DARK SKY COMPLIANT LED HEADS. THE SYSTEM'S PATENTED OPTIC AND GLARE CONTROL TECHNOLOGY. LAMP: LED, 5700K VOLTAGE: 240V MANUFACTURER: MUSCO LIGHTING (7) TLC-LED-1500 SUBSTITUTIONS: OR EQUAL SUBJECT TO REVIEW NO EQUAL
(L2)	*** ***	MUSCO TOTAL LIGHT CONTROL (TLC FOR LED TECHNOLOGY). 80' POLE WITH (6) 1500W HEADS. FULL CUTOFF DARK SKY COMPLIANT LED HEADS. THE SYSTEM'S PATENTED OPTIC AND GLARE CONTROL TECHNOLOGY. LAMP: LED, 5700K VOLTAGE: 240V MANUFACTURER: MUSCO LIGHTING (6) TLC-LED-1500 SUBSTITUTIONS: OR EQUAL SUBJECT TO REVIEW NO EQUAL
(L3)	Ю	4' LED STRIP LIGHT PRODUCING 4,517 LUMENS, COLOR TEMPERATURE 4,000K, FROSTED POLYCARBONTE LENS, MEDIUM DISTRIBUTION, AND CEILING MOUNTED. LAMP: LED, 4000K VOLTAGE: 120/277V MANUFACTURER: LITHONIA VAP-4000LM-FST-MD-MV0LT-GZI0-40K-80CRI SUBSTITUTIONS: OR EQUAL SUBJECT TO REVIEW NO EQUAL



ELECTRICAL LEGEND AUGUST 201



K = KITCHEN EQUIP

H = ELECTRIC HEAT

20C CONTROLLABLE CIRCUIT BREAKER

206 GFI CIRCUIT BREAKER

NOTE: THIS IS A MASTER SYMBOL LIST. IT MAY BE THAT NOT ALL SYMBOLS SHOWN ARE USED WITHIN THIS SET OF PLANS. HEIGHTS GIVEN ARE TO CENTER LINE OF DEVICE.

© 2008-2011 PK ELECTRICAL, INC.

XFMR OR XF TRANSFORMER


-PHASE CONDUCTOR(S)

-PANELBOARD DESIGNATION

PK Electrical, Inc.
681 Sierra Rose Drive, Suite B
Reno, NV 89511

4601 DTC Boulevard, Suite 740

okelectrical.com



04/20/2020

DOUGLAS COUNTY FAIRGROUNE ARENA SPORTS LIGHTING

REVISIONS

SHEET TITLE

ELECTRICAL LEGEND, FIXTURE SCHEDULE & IECC CALCULATIONS

 DRAWN:
 TPT

 CHECKED:
 JEG

 DATE:
 4/15/20

 JOB NUMBER:
 19058

 PROJECT MGR:
 NA

E0.1

ALL CONDUIT SHALL HAVE PULL CORD IF OTHERWISE EMPTY. CONNECT PUMP MOTORS WITH LIQUID

TIGHT FLEXIBLE METAL CONDUIT.

OTHER ARCHITECTURAL, MECHANICAL OR STRUCTURAL WORK. DO NOT SCALE DISTANCES OFF

THE ELECTRICAL DRAWINGS. USE ACTUAL BUILDING DIMENSIONS.

CONTRACTOR SHALL VERIFY THE AVAILABILITY OF ON SITE STORAGE SPACE, IF NO ON SITE STORAGE SPACE IS AVAILABLE THEN THE CONTRACTOR SHALL COVER THE COST FOR OFF SITE STORAGE. MATERIALS STORED AT THE PROJECT SITE THAT BECOMES SOILED WITH CONSTRUCTION DIRT, CONCRETE, OR MOISTURE SHALL BE REMOVED FROM THE SITE AND REPLACED WITH NEW. DO NOT INSTALL SOILED MATERIAL.

INSTALL EQUIPMENT PER MANUFACTURER'S RECOMMENDATIONS. CONFLICTS BETWEEN CONTRACT DOCUMENTS AND THESE RECOMMENDATIONS SHALL BE REFERRED TO ENGINEER FOR REMEDY. ELECTRICAL OR ELECTRONIC EQUIPMENT THAT HAS BEEN DAMAGED, EXPOSED TO WEATHER OR IS, IN THE OPINION OF THE ENGINEER OR ARCHITECT, OTHERWISE UNSUITABLE BECAUSE OF IMPROPER FABRICATION, STORAGE OR INSTALLATION SHALL BE REMOVED AND REPLACED BY

PROVIDE ANCHORS FOR ALL EQUIPMENT, RACEWAYS, HANGERS, ETC. TO SAFELY SUPPORT

WEIGHT OF ITEM INVOLVED PLUS 100% FOR DEAD LOADS, LIVE LOADS SHALL BE CONSIDERED ANCHORS TO CONSIST OF EXPANSION TYPE DEVICES SIMILAR TO "REDHEAD" OR LEAD

USE PRESET ANCHOR STEEL INSERTS IN CONCRETE SLABS. PROVIDE PRESET ANCHOR SIZE AND TYPE FOR ANTICIPATED OR SPECIFIED ROD/BOLT SIZE AND LIVE/DEAD LOAD.

FURNISH 2500 # CONCRETE PADS, 4" HIGH (INTERIOR LOCATIONS) OR 6" HIGH (EXTERIOR LOCATIONS) UNLESS OTHERWISE NOTED, FOR ALL FREESTANDING EQUIPMENT, I.E. SWITCHBOARDS, PANELS, CONTROL PANELS, MOTOR CONTROL CENTERS, TRANSFORMERS, ETC. PADS SHALL HAVE I" X 45° CHAMFERED EDGES, AND SHALL EXTEND 2" TO 4" BEYOND EQUIPMENT MOUNTINGS.

INTERIOR OF ALL CONDUIT, PULLBOXES, JUNCTION BOXES, OUTLET BOXES, AND PANELBOARD BACKBOXES SOILED WITH DIRT AND DEBRIS PRIOR TO INSTALLATION OF WIRING. TOUCH-UP OR RE-PAINT DAMAGED PAINTED FINISHES AS DETERMINED BY THE ENGINEER.

CONTRACTOR SHALL PROVIDE, PRIOR TO FINAL ACCEPTANCE AND OBSERVATION, ONE-SET OF REVISED RECORD ELECTRICAL CONSTRUCTION DOCUMENTS ON REPRODUCIBLE MEDIUM. ALSO

EXACT ROUTING OF ALL CONDUITS LARGER THAN ONE INCH EXACT LOCATION OF ALL SERVICE GROUNDING/ BONDING CONNECTIONS.

RECORD NOTATIONS SHALL BE CLEARLY DRAWN AT A DRAFTING APPEARANCE EQUAL TO THE ORIGINAL DRAWINGS. CONTRACTOR SHALL ALSO PROVIDE ALL OPERATING AND MAINTENANCE

PRIOR TO PLACING IN SERVICES, ALL ELECTRICAL SYSTEMS SHALL BE TESTED FOR OPENS, GROUNDS, AND PHASE ROTATION. THE MAIN SERVICE GROUND AND ALL LOCAL TRANSFORMER MADE GROUNDS SHALL BE MEGGER-TESTED. PROVIDE GFI TESTING FOR SERVICE SWITCHBOARD.

PROVIDE ENGRAVED NAMEPLATES FOR ALL SWITCHBOARDS, PANELS, TRANSFORMERS, DISCONNECTS, MOTOR STARTERS, CONTACTORS, TIME SWITCHES AND CABINETS. NAMEPLATES SHALL BE WHITE LETTERS ON BLACK FOR NORMAL EQUIPMENT AND WHITE LETTERS ON RED FOR EMERGENCY EQUIPMENT. NAMEPLATES SHALL INCLUDE THE FOLLOWING INFORMATION AS

DESIGNATION (I.E. PANEL A); FUNCTION (I.E. AIR HANDLER AH-I); VOLTAGE, PHASE, WIRE (I.E. 480 VOLT, 3 PHASE, 4W); FEEDER SIZE (I.E. 4-#4/0 THWN CU IN 2" C); SOURCE (I.E.

INDICATE SYSTEM VOLTAGE AND CONTAINED CIRCUITS ON OUTSIDE OF BOX COVER. USE SELF-ADHESIVE MARKING TAPE LABELS AT EXPOSED LOCATIONS AND INDELIBLE BLACK MARKER AT CONCEALED BOXES. ALL FIRE ALARM BOXES SHALL HAVE COVERS PAINTED RED. ALL TEMPERATURE CONTROL BOXES SHALL HAVE COVERS PAINTED BLUE. BRANCH CIRCUIT CONDUCTORS SHALL BE IDENTIFIED IN EACH JUNCTION BOX AND PULL BOX

WITH WIRE MARKERS AS MANUFACTURED BY T&B, PANDUIT, 3M, OR IDEAL TO INDICATE

CIRCUIT NUMBERS. JUNCTION BOX COVERS FOR SPECIAL SYSTEMS SHALL BE LABELED WITH SYSTEM NAME AND OTHER IDENTIFICATION AS DIRECTED; FOR EXAMPLE, "FIRE ALARM-ZONE I" WHERE BOXES ARE INSTALLED FLUSH MOUNTED IN FINISHED AREAS OR SURFACE MOUNTED IN UNFINISHED AREAS, LABELING SHALL BE WITH ENGRAVED PLASTIC NAMEPLATE AS SPECIFIED HEREIN. WHERE BOXES ARE INSTALLED ABOVE ACCESSIBLE CEILINGS, LABELING MAY BE NEAT HAND WRITTEN LETTERING WITH INDELIBLE MARKER.

DEVICE PLATES - SMITCHES AND RECEPTACLES: IDENTIFY THE PANELBOARD AND BRANCH CIRCUIT NUMBER FROM WHICH SERVED ON THE FRONT OF THE DEVICE PLATE WITH PERMANENT POLYESTER TAPE. LOCATE ALL LABELS AT THE BOTTOM OF THE PLATE IN THE SAME LOCATION

ALL EXISTING EQUIPMENT REMOVED DURING THE COURSE OF THIS PROJECT SHALL BE OFFERED TO OWNER FOR SALVAGE. ANY EQUIPMENT SELECTED BY OWNER SHALL BE DELIVERED TO OWNER ON SITE. ALL REMAINING EQUIPMENT BECOMES THE PROPERTY OF THIS CONTRACTOR AND SHALL BE

THIS PROJECT IS SUBJECT TO THE SEISMIC BRACING REQUIREMENT OF THE INTERNATIONAL BUILDING CODE, 2012 EDITION. THE FOLLOWING CRITERIA ARE APPLICABLE TO THIS PROJECT: SEISMIC USE GROUP: II; SEISMIC CLASS CATEGORY: D; SEISMIC DESIGN CATEGORY: D. IT IS RECOMMENDED THAT THE CONTRACTOR ENLIST THE SERVICES OF A QUALIFIED SEISMIC

BRACING VENDOR/ SUPPLIER, PROVIDE BRACING FOR IDENTIFIED EQUIPMENT AND SYSTEM. ELECTRICAL EQUIPMENT: ELECTRICAL EQUIPMENT SHALL INCLUDE THE FOLLOWING ITEMS TO THE EXTENT REQUIRED ON THE DRAWINGS OR IN OTHER SECTIONS OF THESE SPECIFICATIONS TO BE

LIGHT FIXTURES, TRANSFORMERS, SWITCHBOARDS, PANELBOARDS. ELECTRICAL SYSTEMS: THE FOLLOWING ELECTRICAL SYSTEMS SHALL BE SEISMICALLY PROTECTED IN ACCORDANCE WITH THIS SPECIFICATION:

CONDUITS REQUIRING NO SPECIAL SEISMIC RESTRAINTS: SEISMIC RESTRAINTS MAY BE OMITTED FROM ELECTRICAL CONDUIT LESS THAN 2-1/2 INCHES TRADE SIZE. ALL OTHER INTERIOR

PK Electrical, Inc.

4601 DTC Boulevard, Suite 740


Reno. NV 89511

Denver, CO 80237 720.481.3290

okelectrical.com

19058

775.826.9010



\mathcal{L}

REVISIONS

SHEET TITLE ELECTRICAL

SPECIFICATIONS

JE6 4/15/20 19058 PROJECT MGR:

SECTION 26 56 00 SPORTS FIELD LIGHTING

PART I - GENERAL

1.01 Related Documents

A. Drawings and general provisions of the bid documents, including general and supplementary conditions apply to this section.

1.02 Description of Work

- A. The Sports Lighting section includes:
 - Galvanized steel luminaire mounting crossarms
 LED Luminaire, with appropriate glare/spill light control
 - 3. Remote driver enclosure
 - 4. Pole Foundation (No direct burial steel pole allowed)
 - 5. Control System
- B. The purpose of this specification is to define the performance standards, product values and features, required manufacturer's service responsibilities, and design standards for the Douglas County Fair Grounds Arena in Gardnerville, NV.

1.03 Submittals

- A. Musco Sports Lighting LLC is the only pre-approved equipment supplier.
- B. All other manufacturers must submit each item in this article according to the conditions of the contract and specification section 10 days prior to bid for consideration. Any deviations to the specification require the manufacturer to list and describe in detail such deviations. Failure to provide this information shall be grounds for immediate rejection.
- C. Submittal information required:
 - 1. Light scans as per Section 1.04 of the specification.
 - 2. Spill scans as per Section 1.05 of the specification.
 - 3. Detailed warranty information as per Section 3.01 of the specification.
 - 4. Detail foundation design as described in Section 2.01
 - Provide written information for the automated control system to include monitoring. Also provide examples of system reporting and access for numbers for personal contact to operate the system.
- Lighting Manufacturer will supply certified photometric reports from Independent Testing Lab (ITL) or a Certified Lab along with an aiming angle summary for verification.

Page 1 of 5

1.04 Sports Lighting Performance

A. Illumination Levels and Design Factors: The illumination levels specified shall be based on light levels for 25 years. Light levels shall not drop below specified targeted lighting levels during the specified warranty period. Appropriate light loss factors shall be applied and submitted for the basis of design.

Area of Lighting	Light Level	Uniformity	# of Points	Size of Area	Grid Spacing
Arena	50 footcandles	2.0:1	61	300' x 200'	30' x 30'
Pens	30 footcandles	8:1	84	N/A	20' x 20'

1.05 Environmental Light Control

A. Light Control Luminaires: All luminaires shall utilize spill light and glare control devices including, but not limited to, internal shields, louvers and external shields. No symmetrical beam patterns are accepted.

B. Spill Light and Glare Control: To minimize impact on adjacent properties, spill light and candela values must not exceed the following levels taken at 3 feet above grade.

	Maximum
50' Specified Spill Line Horizontal Footcandles	.5 fc
50' Specified Spill Line Max Vertical Footcandles	1.5 fc

PART 2 - PRODUCTS

2.01 Pole Structural Steel (Minimum pole height of 80')

- A. The pole shafts shall be high strength low alloy tapered tubular steel that is equal to current ASTM A595 standards, with galvanized coating inside and out. All connections of pole sections shall be by slip fitting the top section over the lower section by a length of at least 1.5 times the diameters.
- B. Steel components of the poles shall be hot dip galvanized t current ASTM A-123. Steel portions of the pole shall be constructed such that all segments of the pole can be readily heated to like temperatures in commercially available galvanizing methods.
- C. To avoid problems of galvanize adherence to differing steel alloys, all steel components used for the pole must be of the same type steel.
- D. All exposed steel components of the pole shall be at least 18" above the surface of the ground to avoid exposure of the steel to the heavily moisture and oxygen laden air, both above and below the surface. There shall be a cap to cover the top of the pole so that rain will not enter the interior of the pole.
- E. To avoid stress corrosion of the pole, there shall be no weld points of the steel portion of the pole within 18" of the ground. The pole shall be galvanized steel.

Page 2 of 5

wind map. Applicable gust factors to be applied per code.

F. The premise of the wind speed criteria will be the 50 year mean recurrent isotach

2.02 Foundation Design

- A. The Manufacturer shall provide a stamped foundation design, prepared by a Structural Engineer, licensed in the State of Nevada.
- B. The foundation design shall be based upon recommendations contained in the Geotechnical Report furnished by the Owner. If a Geotechnical Report is not provided by the Owner, the foundation design shall be based on soils that meet or exceed those of a Class 5 material as defined by the 2018 IBC Table 1806.2.
- C. It is the contractor's responsibility to notify the owner of soil conditions other than the design criteria. The owner shall then be responsible and absorb the additional costs associated with: Providing engineered foundation embedment design by a registered engineer in the State of Nevada for soils other than specified soil conditions. Additional materials required to achieve alternate foundation. No direct burial steel poles allowed.
- D. Lightning Protection: Manufacturer shall provide integrated lightning grounding via concrete encased electrode grounding system as defined by NFPA 780 and be UL Listed per UL 96 and UL 96A. If grounding is not integrated into the structure, the Manufacturer shall supply grounding electrodes, copper down conductors and exothermic weld kits. Electrodes and conductors shall be sized as required by NFPA 780. The grounding electrode shall be not less than 5/8 inch diameter and 8 feet long, with a minimum of 10 feet embedment. Grounding electrode shall be connected to the structure by a grounding electrode conductor with a minimum size of 2 AWG for poles with 75 feet mounting height or less, and 2/0 AWG for poles with more than 75 feet mounting height.

2.03 LED SPORTS LIGHTING FIXTURES

A. The lens is permanently sealed to keep optics away from harmful environmental elements. Fixture is vented and filtered to adapt to environmental elements. Heat sink with a unique convective air cooling design with high thermal conductivity and corrosion resistant construction. Machine mounted surface for maximum heat transfer of diode assembly and maintains low LED junction temperature during high wattage operation. Custom high power diode package with a metal core printed circuit board. The light control visors are factory aimed. Controls and directs more light onto the field which reduced glare and spill and enhances the on-field playability. Fixture is powder coated gray.

2.04 REMOTE ELECTRICAL ENCLOSURE

A. Remote drivers and supporting electrical equipment shall be mounted approximately 10 feet above grade in aluminum enclosures. Drivers are remote for ease of installation and servicing. The enclosures shall be touch-safe and include drivers and fusing with indicator lights on fuses to notify when a fuse is to be replaced for each luminaire. Disconnect per circuit for each pole structure will be located in the enclosure.

Page 3 of 5

2.05 WIRE HARNESS

A. Spiral wound, abrasion protection sleeve, strain relief, plug-in connections

2.06 ENERGY CONSUMPTION

A. The average kWh consumption for the entire facility shall not exceed 39kW.

2.07 CONTROLS AND MONITORING SYSTEM

- A. Factory assembled lighting control cabinet (LCC) The LCC shall be assembled and wired by a UL listed panel builder. The LCC shall contain Contactors, Monitoring and Control System and door mounted Manual off-on-auto selector switches. The LCC shall arrive at the job site ready to attach to an existing wall, switchgear, or a free standing enclosure.
 - i. Control Wire Terminations The Control Wire Terminations shall include UL listed terminal blocks mounted on a DIN rail and 250 volt, 16 amp, touch safe type fuse holders.
 - The ECE shall be constructed of aluminum and shall be powder coated gray. The cabinet door shall utilize a lockable, 3 point latching assembly that provides a NEMA 4 rated seal.
 - iii. Contactor Modules Contactors shall be UL listed for lighting applications. They shall be rated at full capacity, be electrically held, utilize a 120 volt coil and be rated for operation in a ambient temperature range from -40 degrees C to +70 degrees C.
 - iv. Manual off-on-auto Selector Switches For on site manual control, three position selector switches shall be factory mounted to the ECE door. The switches shall be keyed and maintain position, with make before break contacts. The switches shall be factory wired to control terminal blocks.
 - v. Warranty The LCC shall be covered under the standard warranty for the accompanying lighting equipment.
- B. Remote Monitoring System: System shall monitor lighting performance and notify manufacturer if individual luminaire outage is detected so that appropriate maintenance can be scheduled. The manufacturer shall notify the owner of outages within 24 hours, or the next business day. The controller shall determine switch position (manual or auto) and contactor status (open or closed). The Monitoring System shall be factory wired to control terminal blocks.
- Remote Lighting Control System: The Lighting Control System shall allow owners and users with a security code to schedule on/off system operation via a web site, phone, fax or email up to ten years in advance. Manufacturer shall provide and maintain a two-way TCP/IP communication link. Trained staff shall be available 24/7 to provide scheduling support and assist with reporting needs. The Light Control System shall be factory wired to control terminal blocks

Page 4 of 5

PART 2 - EXECUTION

3.01 Warranty

- A. 25-Year Warranty: Each manufacturer shall supply a signed warranty covering the entire system for 25 years from the date of shipment. Warranty shall guarantee specified light levels. Manufacturer shall maintain specifically-funded financial reserves to assure fulfillment of the warranty for the full term. Warranty does not cover weather conditions events such as lightning or hail damage, improper installation, vandalism or abuse, unauthorized repairs or alterations, or product made by other manufacturers.
- B. Maintenance: Manufacturer shall monitor the performance of the lighting system, including on/off status, hours of usage and luminaire outage for 25 years from the date of equipment shipment. Parts and labor shall be covered such that individual luminaire outages will be repaired when the usage of any field is materially impacted. Manufacturer is responsible for removal and replacement of failed luminaires, including all parts, labor, shipping, and equipment rental associated with maintenance. Owner agrees to check fuses in the event of a luminaire outage.

3.02 Field Technician

A. Manufacturer shall have available a local factory trained technician to provide project support including but not limited to: Lamp replacement, confirm luminaire, aiming points, troubleshoot, and educate customer maintenance personnel.

Page 5 of 5


DV Florings I to

PK Electrical, Inc. 681 Sierra Rose Drive, Suite B Reno, NV 89511 775.826.9010

4601 DTC Boulevard, Suite 740 Denver, CO 80237 720.481.3290

okelectrical.com

19058



OUGLAS COUNTY FAIRGROUND
ARENA SPORTS LIGHTING

REVISIONS

SHEET TITLE
SPORTS FIELD LIGHTING

SPECIFICATIONS

 DRAWN:
 TPT

 CHECKED:
 JEG

 DATE:
 4/15/20

 JOB NUMBER:
 19058

 PROJECT MGR:
 NA

E0.2B

20-Api	r-20		PA	NEL:	M	SB		LO	CATION:	ELECTRICAL A	REA
TYPE	DESCRIPTION	LOAD	BKR	CIR	Α	В	CIR	BKR	LOAD	DESCRIPTION	TYPI
L	MUSCO FIXTURE 'POLE #1'	6204	70/2	1	11964		2	60/2	5760	PNL BOOTH	E
L	X	6204	X	3		11964	4	Х	5760	X	Ε
L	MUSCO FIXTURE 'POLE #2'	6204	70/2	5	7764		6	20/2	1560	WELL PUMP HOUSE & TELM	Е
L	X	6204	X	7		7764	8	Х	1560	X	Ε
L	MUSCO FIXTURE 'POLE #3'	5316	60/2	9	5516		10	20	200	SPRINKLER CONTROL	E
L	X	5316	Х	11		5580	12	20	264	BLEACHER CANOPY LIGHTS	L
L	MUSCO FIXTURE 'POLE #4'	5316	60/2	13	5316		14	20		SPARE	
L	X	5316	Х	15		5316	16	20		SPARE	
L	MUSCO CONTACTOR	180	20	17	180		18	20		SPARE	
	SPACE			19		0	20	20		SPARE	
					30740	30624	T				
	PER BUS SIZE:	600			GROUND:	30624		NDARD		NOTES:	
VOLT	AGE:	240			GROUND: MOUNTING:	30624	SURI	FACE		NOTES: NEW SWITCHBOARD	
VOLT.	AGE: EE:	240 1			GROUND: MOUNTING: ENCLOSURE:		SUR!	FACE			
VOLT PHAS WIRE:	AGE: EE: :	240 1 3			GROUND: MOUNTING: ENCLOSURE: # OF 1-POLE	CIRCUITS	SURI	A 3R			
VOLT PHAS WIRE: LUGS	AGE: EE: :	240 1 3 MCB			GROUND: MOUNTING: ENCLOSURE: # OF 1-POLE (CONNECTED	CIRCUITS KVA:	SUR!	A 3R	61.4		
VOLT PHAS WIRE: LUGS BREA	AGE: SE: : : KER AIC RATING:	240 1 3 MCB 65K			GROUND: MOUNTING: ENCLOSURE: # OF 1-POLE (CONNECTED)	CIRCUITS KVA:	SUR!	A 3R	61.4 255.7		
VOLT. PHAS WIRE: LUGS BREA NEUTI	AGE: SE: : : KER AIC RATING:	240 1 3 MCB			GROUND: MOUNTING: ENCLOSURE: # OF 1-POLE (CONNECTED	CIRCUITS KVA:	SUR!	A 3R	61.4		

3/4"

3/4"

3/4"

3/4"

1 1/4"

| |/4"

| |/4"

1 1/2"

1 1/2"

2"

2 1/2"

2 1/2"

(2) 2 1/2"

(2) 3"

(2) 4"

(3) 3"

(3) 4"

(5) 4"

FEEDER SCHEDULE (600V, 1Ø, 3W)

153

203

303

403

503

603

703

803

1003

1253

1503

1753

2003

2253

25*0*3

3003

35*0*3

4003

5003

6003

8003

10003

12003

16003

20003

20

70

80

100

125

150

175

200

225

25*0*

300

400

500

600

800

1000

1200

1600

2000

FEEDER AMPERE WIRE (CU) BOND (CU) CONDUIT

(3) 12

(3) 12

(3) 10

(3) 8

(3) 6

(3) 4

(3) 3

(3) 2

(3) 1/0

(3) 1/0

(3) 2/0

(3) 3/0

(3) 4/0

(3) 25*0*K

(3) 350K

(3) 400K

(3) 500K

(6) 250K

(6) 350K

(6) 500K

(9) 400K

(9) 600K

(12) 600K

(15) 600K

(2) 2

(2) |

(2) 1/0

(3) 2/0

(3) 3/0

(4) 4/0

(5) 25*0*K

AL A	REA
	TYPE
	Е
	E E
TELM	E
	E E
IGHTS	L

GENERAL NOTES

NOTED OTHERWISE.


(E) AND/OR HALFTONE LINES INDICATE EXISTING EQUIPMENT, (X) AND/OR DASHED LINES INDICATE

EXISTING EQUIPMENT TO BE REMOVED, (N) AND/OR SOLID LINES INDICATE NEW EQUIPMENT UNLESS

ALL CONTRACTOR PROVIDED EQUIPMENT SHALL COMPLY WITH NV ENERGY SPECIFICATIONS AND REQUIREMENTS.


ALL CONDUCTOR SIZES ARE BASED ON COPPER. ALUMINUM IS NOT PERMITTED.

4			
-			
-			
-			
4			
-			
4			
-			






- CONTRACTOR SHALL DISCONNECT AND PULL BACK ALL CONDUCTORS FROM DEMOLISHED SWITCHBOARD TO NEW 'MSB'.
- 2 PROVIDE CONCRETE EQUIPMENT PAD PER DIVISION SPECIFICATIONS TO SATISFY MANUFACTURER'S REQUIREMENTS.
- CONTRACTOR SHALL UTILIZE ALL EXISTING CONDUCTORS AND FEED CONDUITS TO NEW SWITCHBOARD. IF EXISTING CONDUCTORS ARE OF INSUFFICIENT LENGTH TO REACH NEW BREAKER LOCATIONS, NEW CONDUCTORS SHALL BE INSTALLED.
- 4 SEE SITE PLAN FOR CONDUIT AND WIRE SIZE.











GLAS COUNTY FAIRGROUNDS ARENA SPORTS LIGHTING

REVISIONS

SHEET TITLE
ONELINE DIAGRAMS
AND PANEL SCHEDULE

 DRAWN:
 TPT

 CHECKED:
 JEG

 DATE:
 4/15/20


 JOB NUMBER:
 19058

 PROJECT MGR:
 NA


E0.3

N-9 CONCRETE BOX


SCALE: NONE




6" DIA. GROUTED



E0.4











PK Electrical, Inc. 681 Sierra Rose Drive, Suite B Reno, NV 89511 775.826.9010





FAIRGROUNDS

REVISIONS

SHEET TITLE

JE6 4/15/20 19058 PROJECT MGR:

- EXISTING ARENA FIXTURE AND POLE SHALL BE DISCONNECTED AND REMOVED IN ITS ENTIRETY. EXISTING CONDUIT AND CONDUCTORS REMOVED BACK TO NEAREST SOURCE.
- CONTRACTOR SHALL INTERCEPT EXISTING CONDUIT FEED FROM 'CDP' TO PANEL 'BOOTH' AND REDIRECT TO NEW SWITCHBOARD.
- REMOVE BARRICADE POST AROUND UTILITY TRANSFORMER WHEN DISCONNECTING EXISTING CONDUIT FROM DEMOLISHED GEAR. MAINTAIN 3'-6" CLEARANCE IN FRONT OF NEW SWITCHBOARD AND PROPERLY LAYOUT NEW BOLLARDS IN PLACE TO ASSURE NEW SWITCHBOARD DOOR SWING SHALL HAVE PROPER CLEARANCE.
- (4) CONTRACTOR SHALL UTILIZE PORTION OF EXISTING EQUIPMENT SUPPORT SYSTEM FOR MOUNTING OF NEW LIGHTING CONTROL PANEL. CONTRACTOR SHALL DEMO AND REMOVE ALL REMAINING SUPPORTS SYSTEM NOT UTILIZED.


GENERAL NOTES

I. (X) AND/OR DASHED LINES INDICATE EXISTING EQUIPMENT TO BE REMOVED, (E) AND/OR HALFTONE LINES INDICATE EXISTING EQUIPMENT TO REMAIN UNLESS NOTED OTHERWISE.

2. SALVAGEABLE ITEMS REMOVED DURING DEMOLITION SHALL BE OFFERED TO OWNER PRIOR TO DISPOSAL OR REMOVAL FROM SITE.

3. EXISTING CIRCUITS AND POLE LOCATIONS AS INDICATED ARE BASED ON CASUAL FIELD OBSERVATION AND INFORMATION PER RECORD DRAWINGS AND SHALL BE FIELD VERIFIED BY ELECTRICAL CONTRACTOR PRIOR TO START OF DEMOLITION WORK.

4. THE CONTRACTOR SHALL SALVAGE AND REUSE EXISTING BOXES AND CONDUIT WHERE POSSIBLE. DAMAGED CONDUIT, FITTINGS BOXES, ETC. MAY NOT BE RE-USED. NEW CIRCUITING AS INDICATED ON THE DRAWINGS IS SHOWN FOR INTENT ONLY AND MAY VARY BASED ON ACTUAL FIELD CONDITIONS (NEW CIRCUITING SHALL MATCH EXISTING WHERE POSSIBLE TO UTILIZE EXISTING HOME-RUN CONDUITS, ETC.). KEEP AS-BUILT DRAWINGS CURRENT WITH ANY DEVIATION IN CIRCUITING FROM WHAT IS INDICATED WITHIN THESE PLANS.








PK Electrical, Inc.

681 Sierra Rose Drive, Suite B Reno, NV 89511 775.826.9010 4601 DTC Boulevard, Suite 740 Denver, CO 80237 720.481.3290 pkelectrical.com

19058



RGROUNDS

ARENA SPORTS LIGI

REVISIONS

SHEET TITLE

SITE LIGHTING DEMOLITION PLAN

 DRAWN:
 TPT

 CHECKED:
 JEG

 DATE:
 4/15/20

 JOB NUMBER:
 19058

 PROJECT MGR:
 NA

E1.1


- 2 SWITCH TO BE PLACED IN ANNOUNCER BOOTH TO CONTROL BLEACHER CANOPY LIGHTING. COORDINATE FINAL LOCATION WITH PARKS AND RECREATION PRIOR TO FINAL ROUGH-IN.
- 3 | SURFACE MOUNT FIXTURES TO CANOPY SUPPORT STRUCTURE.

| WIRE SIZED FOR VOLTAGE DROP, ENTIRE CIRCUIT.

- (4) INSTALL BARRICADE POST AROUND EXISTING UTILITY TRANSFORMER AND NEW SWITCHBOARD UPON COMPLETION OF NEW WORK. MAINTAIN 3'-6" CLEARANCE IN FRONT OF NEW SWITCHBOARD AND PROPERLY LAYOUT NEW BARACADE POST BOLLARDS IN PLACE TO ASSURE NEW SWITCHBOARD DOOR SWING SHALL HAVE PROPER CLEARANCE.
- 5 AT PULLBOX REDUCE WIRE SIZE TO POLE LIGHT FIXTURE TO 1" C. W (2) #6 \$ #106.

GENERAL NOTES

- (E) AND/OR HALFTONE LINES INDICATE EXISTING EQUIPMENT, (N) AND/OR SOLID LINES INDICATE NEW EQUIPMENT UNLESS NOTED OTHERWISE.
- 2. | SEE ONELINE DIAGRAM(S) FOR CONDUIT, WIRE SIZES AND EQUIPMENT REQUIREMENTS.
- 3. IT IS THE CONTRACTOR'S RESPONSIBILITY TO CALL I-800-227-2600 FOR LOCATES PRIOR TO DIGGING. IT IS ALSO THE CONTRACTORS RESPONSIBILITY TO LOCATE ALL NON-UTILITY UNDERGROUND ITEMS.
- 4. REPAIR AND REPLACE ALL LANDSCAPING AND SITEMORK DISTURBED BY EXCAVATION INCLUDING BUT NOT LIMITED TO IRRIGATION LINES, LAWNS, PLANTING, ETC.



PK Electrical, Inc.

681 Sierra Rose Drive, Suite B Reno, NV 89511 775.826.9010

4601 DTC Boulevard, Suite 740 Denver, CO 80237 720.481.3290

pkelectrical.com 19058

COUND

REVISIONS

SHEET TITLE NEW WORK SITE LIGHTING PLAN

DRAWN:	TP
CHECKED:	JE
DATE:	4/15/2
JOB NUMBER:	1905
PROJECT MGR:	N

